

## DJM-909 Profession 2-Channel Mixer with Effects

### Features

- 2 Channels
- 4 Line Inputs
- 2 Turntable Inputs
- 2 Switchable Phono/Line Inputs
- 2 Fader Start Inputs
- 3 Band EQ per channel(-26dB to +6dB)
- EQ On/Off switch
- 1 Mic Input (Neutric / 1/4" combo)
- 2 Band Mic EQ
- Touch Sensitive Screen for Effects and Fader Curve
- Effect Lock / On / Off Switches
- Footswitch Connection for Effects
- Transform switches
- Reverse switches
- Non-Contact Crossfader
- Adjustable Channel Fader curve
- Independantly Adjustable Cross Fader Curve
- Adjustable Cross Fader Lag
- Adjustable Cross Fader Tension
- BPM Tap Buttons
- Headphone Monitor auditioning
- Session inputs / outputs with level control
- Reinforced headphone jacks
- Stereo Send / Return
- RCA & XLR Outputs



### Specs

- General Power requirements:** AC 120V, 60 Hz
- Power consumption:** 31W
- Weight:** 6.5kg / 14lbs 5oz.
- Dimensions:** 9-7/8" (W) x 15" (D) x 4-1/4" (H)
- Audio Section**Frequency response: 20Hz to 20kHz (CD)
- Signal-to-noise ratio:** 93 dB or more
- Distortion Ratio:** 0.02% or less
- Specifications and design are subject to possible modification without notice.**